



SECONDS / MINUTES	ON TIME		OFF TIME	
	OFF	ON	OFF	ON
.1	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
.2	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
.4	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
.8	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
1.6	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
3.2	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
6.4	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
12.8	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
25.6	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
51.2	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

ADD ON TIME SELECTIONS
6.3 SECONDS OR MINUTES

IN ADDITION TO ACTUATOR CYCLE TIME

AVAILABLE SPEED OPTIONS:

MODEL

TIMING

CTBA12	ON .1 TO 102.3 SEC., OFF 1 TO 102.3 MIN.
CTBA13	ON .1 TO 102.3 SEC., OFF 1 TO 102.3 MIN.
CTBA22	ON .1 TO 102.3 MIN., OFF 1 TO 102.3 MIN.
CTBA23	ON .1 TO 102.3 MIN., OFF 1 TO 102.3 MIN.
CTBA33	ON 1 TO 102.3 MIN., OFF 1 TO 102.3 MIN.
CTBA44	ON .25 TO 255.75 HRS., OFF .25 TO 255.75 HRS.

OPERATION:

CONNECTION:

SUPPLY POWER TO T1 & T2
T3 & T4 SUPPLIED FOR LIGHT INDICATION.

WHEN SPST SWITCH IS CLOSED THE ACTUATOR IS ACTIVATED AND WILL OPEN AND CLOSE AS SET USING THE DIP SWITCHES ON THE TIMER. THE CYCLE WILL REPEAT UNTIL POWER IS DISCONNECTED.

ICI

Indelac Controls, Inc.

WIRING DIAGRAM FOR ELECTRIC ACTUATOR WITH TIMER

JLR 3-26-02

040204